





#### LISTED 94 05 TEMP.IND. & COULS

Technical Data		FSAFB24-SR. FSAFB24-SR-S	
Power supply		24 VAC ±20%, 50/60 Hz	
		24 VDC +20% / -10%	
Power consumption run	nning	6 W, 8.5 VA	
ha	lding	3 W, 5 VA	
Transformer sizing		10 VA (class 2 power source)	
Electrical connection		3 ft, 18 GA appliance cable, 1/2" conduit	
		connector	
		-S models: two 3 ft, 18 gauge appliance cables	
		with 1/2" conduit connectors	
Overload protection		electronic throughout 0 to 95° rotation	
Operating range Y		2 to 10 VDC, 4 to 20mA	
Input impedance		100 k $\Omega$ for 2 to 10 VDC (draws 0.1 mA)	
		$500 \Omega$ for 4 to 20 mA	
Feedback output U		2 to 10 VDC (max. 0.5 mA)	
Torque		180 in-lb [10 Nm] minimum	
Direction of rotation s	pring	reversible with CW/CCW mounting	
r	notor	reversible with built-in switch	
Mechanical angle of rotation		95° (adjustable with mechanical end stop, 35° to	
Dunning time	nrina	95 <sup>-</sup> )	
Running unie S	pring	< 20 Seconds @ -4 F to 122 F [-20 C to 50 C];	
r	notor	< 00 Seconds at 250°E < 75 seconds at 70°E	
Override control	110101	Short 3 to Hot (2) to override 100% open	
Position indication		visual indicator 0° to 95°	
		$(0^{\circ} \text{ is full spring return position})$	
Manual override		5 mm hex crank ( <sup>3</sup> / <sub>16</sub> " Allen), supplied	
Humidity		max. 95% RH non-condensing	
Ambient temperature		-22°F to 122°F [-30°C to 50°C]	
Storage temperature		-40°F to 176°F [-40°C to 80°C]	
Housing		Nema 2, IP54, Enclosure Type2	
Housing material		zinc coated metal and plastic casing	
Agency listings+		cULus acc. to UL60730-1A/-2-14, CAN/CSA	
		E60730-1:02, CE acc. to 2004/108/EC &	
		2006/95/EC	
Noise level		$\leq$ 40dB(A) motor @ 70 seconds, run time dependent	
		≤62dB(A) spring return	
		inaudible holding	
Servicing		maintenance free	
Quality standard			
Weight		4.6 lbs (2.1 kg); 4.9 lbs (2.25 kg) with switches	
Factor impulse voltage ouvy, type of action 1.44 (1.44.B for -S version), control Pollution Degree 3.			
Auxiliary switches		2 x SPDT 3A resistive (0.5A inductive) @ 120 or	
Auxiliary Switchios		$250$ VAC. UI approved one set at $\pm 10^{\circ}$	
		one adjustable 10° to 90°	

# FSAFB24-SR, FSAFB24-SR-S

Fire & Smoke, Fail-Safe, Spring Return, Proportional 2-10 VDC Actuators

Torque min. 180 in-lb Control 2 to 10 VDC Feedback 2 to 10 VDC

## Application

For proportional control of fire and smoke combination and smoke dampers in UL555S applications. In new installations, codes require damper manufacturer mounting per UL555S.

## Operation

The FSAFB24-SR, FSAFB24-SR-S actuator provides 95° of rotation and is provided with a graduated position indicator showing 0° to 95°. The actuator will synchronize the 0° mechanical stop or the physical damper and use this point for its zero position during normal control operations. A unique manual override allows the setting of any actuator position within its 95° of rotation with no power applied. This mechanism can be released physically by the use of a crank supplied with the actuator. When power is applied the manual override is released and the actuator drives toward the fail-safe position.

The actuator uses a brushless DC motor which is controlled by an Application Specific Integrated Circuit (ASIC) and a microprocessor. The microprocessor provides the intelligence to the ASIC to provide a constant rotation rate and to know the actuator's exact position. The ASIC monitors and controls the brushless DC motor's rotation and provides a Digital Rotation Sensing (DRS) function to prevent damage to the actuator in a stall condition. The position feedback signal is generated without the need for mechanical feedback potentiometers using DRS. The actuator may be stalled anywhere in its normal rotation without the need of mechanical end switches. The actuator cannot burn out from being stalled before full rotation is achieved.

The FSAFB24-SR, FSAFB24-SR-S is mounted directly to control shafts up to 1.05" diameter by means of its universal clamp and anti-rotation bracket. A crank arm and several mounting brackets are available for damper applications where the actuator cannot be direct coupled to the damper shaft. The spring return system provides the specified torque to the application during a power interruption. The FSAFB24-SR, FSAFB24-SR-S actuator is shipped at +5° (5° from full fail-safe) to provide automatic compression against damper gaskets for tight shut-off.



# FSAFB24-SR, FSAFB24-SR-S

# Fire & Smoke, Fail-Safe, Spring Return, Proportional 2-10 VDC Actuators

Accessories			
AV 8-25	Shaft extension		
IND-AFB	Damper position indicator		
KH-AFB	Crank arm		
K7-2	Universal clamp for up to 1.05" dia jackshafts		
TF-CC US	Conduit fitting		
Tool-06	8mm and 10 mm wrench		
ZG-100	Universal mounting bracket		
ZG-101	Universal mounting bracket		
ZG-118	Mounting bracket for Barber Colman <sup>®</sup> MA 3/4, Honeywell <sup>®</sup> Mod III or IV or Johnson <sup>®</sup> Series 100 replacement or new crank arm type installations		
ZG-AFB	Crank arm adaptor kit		
ZG-AFB118	Crank arm adaptor kit		
ZS-100	Weather shield (metal)		
ZS-150	Weather shield (polycarbonate)		
ZS-260	Explosion-proof housing		
ZS-300	NEMA 4X housing		
NOTE: When using F	SAFB24-SR and FSAFB24-SR-S actuators, only use accessories listed on this		

**NOTE:** When using FSAFB24-SR and FSAFB24-SR-S actuators, only use accessories listed on this page. For actuator wiring information and diagrams, refer to Belimo Wiring Guide.

### **Typical Specification**

Proportional fire and smoke spring return damper actuators shall be direct coupled type which require no crank arm and linkage and be capable of direct mounting to a jackshaft up to a 1.05" diameter. A manual override shall be provided for positioning the damper open before power is available on a new construction project. The actuator must provide proportional damper control in response to a 2 to 10 VDC or, with the addition of a  $500\Omega$  resistor, a 4 to 20 mA control input from an electronic controller or positioner. Control wiring shall conform to Belimo Americas wiring schematics. The actuators shall be a flip-over design so that they may be used for either clockwise or counterclockwise fail-safe operation. Actuators shall use a brushless DC motor controlled by a microprocessor and be protected from overload at all angles of rotation. Run time shall be constant, and independent of torque. A 2 to 10 VDC feedback signal shall be provided for position feedback. Actuators shall be cULus listed, have a 5 year warranty and be manufactured under ISO 9001 International Quality Control Standards. Actuators shall be as manufactured by Belimo.

## Wiring Diagrams

# 🔀 INSTALLATION NOTES

Provide overload protection and disconnect as required.

#### **CAUTION** Equipment Damage!

Actuators may be connected in parallel if not mechanically mounted to the same shaft. Power consumption and input impedance must be observed.

Actuator may also be powered by 24 VDC.

# APPLICATION NOTES

Meets UL requirements without the need of an electrical ground connection.

The ZG-R01 500  $\Omega$  resistor may be used.

#### WARNING Live Electrical Components!

During installation, testing, servicing and troubleshooting of this product, it may be necessary to work with live electrical components. Have a qualified licensed electrician or other individual who has been properly trained in handling live electrical components perform these tasks. Failure to follow all electrical safety precautions when exposed to live electrical components could result in death or serious injury.

#### Safety Note:

Screw a conduit fitting into the actuator's metal bushing. Jacket the actuator's input and output wiring with suitable flexible conduit. Properly terminate the conduit in a suitable junction box.



Smoke Detector or Relay from area

smoke detection system



BFI

F&S Damper

Auxiliary Switches for FSAFB24-SR-S



#### Applications

For mounting instructions visit:

https://www.belimo.us/bellib/Damper\_Actuators/AFB\_NFB\_Installation.pdf

### **Parallel Wiring**



Only one smoke signal &/or one thermal sensor may be employed for parallel actuators.

Fire & Smoke, Fail-Safe, Spring Return, Proportional 2-10 VDC Actuators

Any wire 5 FBK could be used to indicate position or to drive other actuators.



## Underfloor Air Conditioning



# FSAFB24-SR, FSAFB24-SR-S

Fire & Smoke, Fail-Safe, Spring Return, Proportional 2-10 VDC Actuators



Stairwell Pressurization



# Economizer with reopenable dampers

FSAFB24-SR-S Sequence of Operation OA RA MA In normal conditions, 1 and 2 of actuator receive 24V and actuator responds to the 2-10V signal placed on 3. Power R1 1235 1235 1 2 3 5 to drive full open. Shorting 24V hot to wire 3 causes actuator to drive open. Connection to signal is broken to prevent 24V hot from damaging controller. This also bypasses R2, the freezestat, and the 165°F primary sensor. This would achieve the typical fire fighters' control system (FSCS) panel bypass to open a damper. R1-1 R2 Signal -//---2-10V Control Unccupied or other limit. Com Damper or actuator FΖ auxiliary switches not The 250°F secondary sensor cuts power to 1 shown. Since this is an and regardless of other controls, closes dampers. engineered smoke 165°F <sup>1</sup>R1-2 Sensors are manual reset. If R1 is normal, 250°F control system, the power R2 to open signal to 3. This causes **FSCS** must receive actuators to see 0V signal and they drive closed. Indication. FZ is freezestat or relay. It is bypassed by R1-2. The secondary 250°F sensor is not overridden by R1 per UL555S. However, Fire Marshal or Com Hot Transformer Building Official should indicate required results. The smoke control system may need to have final control.

(Typical for many proportional applications.)